

Small Instrumentation Modules

SIM964 — 1 MHz analog limiter

- Settable upper & lower limits (± 10 V)
- 10 mV resolution
- 1 MHz bandwidth
- TTL outputs for limit detecting
- High slew rate

• SIM964 ... \$1595 (U.S. list)



SIM964 Analog Limiter

The SIM964 Analog Limiter provides upper and lower voltage limits for conditioning dynamic signals. Limits are set between ± 10 V with 10 mV resolution. Two rear-panel TTL signals are activated when upper or lower limits are exceeded. The SIM964 uses SRS's clock-stopping architecture design to eliminate digital noise artifacts. The low output noise and low harmonic distortion of the SIM964 make it ideal for many applications.

Specifications

Limit settings	± 10 V (both upper and lower)
Resolution	10 mV
Bandwidth	1 MHz
Limit type	Soft limit (100 mV range)
Input impedance	1 M Ω
Output noise	<400 μ Vrms
THD	0.01 % (80 dB) at 1 kHz
Slew rate	20 V/ μ s

Limit detect	TTL level signals (rear-panel BNC connectors) are low when upper or lower limits are exceeded.
Operating temperature	0°C to 40°C, non-condensing
Interface	Serial via SIM interface
Connectors	BNC (2 front, 2 rear) DB15 (male) SIM interface
Power	Powered by SIM900 Mainframe, or by user-provided DC power supply (± 15 V and +5 V)
Dimensions	1.5" \times 3.6" \times 7.0" (WHD)
Weight	1.5 lbs.
Warranty	One year parts and labor on defects in materials and workmanship

Ordering Information

SIM964 Programmable analog limiter \$1595